

AM.3.RD / AM.3.SD...

SCREWS AND STUDS

Ch. IV page 21

ORDERING CODE

AM

Modular valve

3

CETOP 3/NG6

RD = Direct pressure reducing valve SD = Direct pressure sequencing valve

*

Control on lines

AM.3.RD version = A / P AM.3.SD version = P

1 = Positive overlap

2 = Negative overlap

Omit for version AM3SD

Type of adjustment

C = Grub screw V = Handwheel

Setting ranges

 $1 = \text{max. } 2 \div 30 \text{ bar (white spring)}$

2 = max. 10 ÷ 120 bar (yellow spring)

 $3 = \text{max. } 60 \div 250 \text{ bar (green spring)}$

**

00 = No variant

V1 = Viton

4


Serial No.


AM.3.RD... /AM.3.SD... MODULAR PRESSURE REDUCING / PRESSURE SEQUENCING VALVES CETOP 3

AM3RD and AM3SD valves are direct acting spool type pressure reducing and sequencing units, respectively, with one end pre-loaded by means of a spring an the other end exposed to the hydraulic pressure.

The drainage is drained within the valve to port T. Pressure is adjustable by means of a screw and locknut, or of a handwheel. Three types of springs allow adjustment within the range 2÷250 bar. The pressure reducing valves are available in two versions: with positive overlap (suitable with low flow rate) and with negative overlap to obtain a greater pressure reinstatement speed.

Max. operating pressure: port P 350 bar Max. pressure adjustable 250 bar 2 ÷ 30 bar Setting ranges: spring 1 spring 2 10 ÷ 120 bar spring 3 60 ÷ 250 bar Max. flow 40 l/min Internal drainage RD: Positive overlap version 0.5 l/min Negative overlap version 2 l/min Hydraulic fluids Mineral oils DIN 51524 Fluid viscosity $10 \div 500 \text{ mm}^2/\text{s}$ Fluid temperature -25°C ÷ 75°C Ambient temperature $-25^{\circ}\text{C} \div 60^{\circ}\text{C}$ Max. contamination level class 10 in accordance with NAS 1638 with filter $\beta_{25} \ge 75$ Weight 1,3 Kg





The fluid used is a mineral based oil with a viscosity of 46 mm²/sec at 40 degrees C. The tests have been carried out at with a fluid temperature of 40 degrees C.

OVERALL DIMENSIONS

